

ENGLISH

User Manual

OMNIA G65

Series

GaN 65W Fast charging Power Strip

Specification

Description: GaN 65W Fast charging Power Strip

Rated Voltage, Frequency, Current:  
AC 125V, 50-60Hz, 15A

Rated Capacity: 1650W MAX

USB Input: AC 110V, 50-60Hz, 1.5A max.

USB Total Output: 65W max.

USB Output Power:

- USB-C1 / C2 PD: 5-11V≒2.8A(PPS) ; 5-20V≒2.8A(PPS), 5V≒3A; 9V≒3A; 12V≒3A 15V≒3A; 20V≒3.25A
- USB-A1 / A2 QC: 5V≒3A; 9V≒3A; 12V≒3A
- USB-C1 + C2 / USB-C1 + A2: 45W + 20W
- USB-A1 + A2 / USB-A1 + C2: 36W + 20W
- USB-C1 + A1 / USB-C2 + A2: 15W(5V≒3A)
- USB-C1 + (USB-C2 + A2): 45W + 15W
- USB-A1 + (USB-C2 + A2): 36W + 15W
- (USB-C1 + A1)+USB-C2: 15W + 20W
- (USB-C1 + A1)+USB-A2: 15W + 20W
- (USB-C1 + A1)+(USB-C2 + A2): 15W + 15W

Operating Temperature: 0°C - 40°C

Size: 210 x 58 x 31.4 mm    Weight: 517 g

Power Cord Length: 1.8m    Warranty: 3 years

\*The ground wire of this product is a green wire.

Items Included

- OMNIA G65 x1
- Velcro Strap x2
- 3M power Strip Holder
- User Manual

Product Introduction

4-outlet power strip with GaN 65W USB fast charging ports charges multiple devices simultaneously.

High Power Safety Cord  
VCTF 2.0mm\* double-layer insulation coated wire is used, which meets the national safety standard.

PC Flame Retardant Material  
Resistant to high temperature, flame retardant and fireproof.

Master & Overload Automatic Power-off Switch  
When overloaded, it will automatically cut off the power. Please remove high-power-consuming devices, and switch to the RESET position after a few minutes before it can be used normally.

Dust-Proof & Child Safety Shutter  
Keep children from touching the socket and prevent dust from entering

2 USB-C + 2 USB-A Ports  
Multiple devices can be charged simultaneously

MacBook Pro 13" & USB-C 65W Laptops

iOS & Android Devices

Game Console

Power Bank

Lightning Surge Protection  
It can absorb lightning strikes and other abnormalities to generate a high-voltage current pulse, stabilize the power supply, and protect the safety of electrical appliances.

Independent Push Switch  
Avoid accidental touch.

PTP Indicator Light (Proactive Thermal Protector)  
Indicator light on to show your devices are powered on and protected.  
When the light is on, the socket is normally powered. When the socket or switch is abnormally high temperature and has not reached the ignition point, the PTP high-temperature power-off protection function will be activated, and the power-on indicator light will go out. When PTP is activated, the socket is damaged and can no longer be used.

Keyholes for wall mounting

Surge Protection Device

Surge Absorption Voltage: 2500V max. (1.2/50μs)  
Surge Absorption Current: 1200A max. (8/20μs)  
Surge Absorption Energy: 25J max. (10/1000μs)  
\*If the surge exceeds the maximum absorption, the surge absorber will be damaged, which means the electrical appliance cannot be protected.

Smart Charge IC chip  
Smart charging: The current / voltage required for the device is identified automatically for fast charging.  
Other devices: Up to 1.5A charging current is provided if USB BC1.2 charging specifications are met.  
If the equipment has no charging protocol, USB-A supports DCP MODE and provides 1.0A (normal output mode) (USB-C does not support charging without protocol).

Warning  
1. The total power of electrical appliances used at the same time on the socket of the same extension cord shall not exceed 1650W, so as to avoid overload and cause a fire.  
2. This product is only for indoor use in a dry place to reduce the risk of electric shock.  
3. This product can only be used with AC110V power supply, and must not exceed 125V to avoid damage to electrical equipment.  
4. Please check the extension cord switch and socket regularly. If there is any abnormal condition such as damage, green rust, coking or overheating, stop using it immediately and replace it.  
5. When the PTP is activated, the switch cannot be positioned at the ON position. Do not apply external force to avoid serious danger.

The instruction for using power strip holder of extension cord  
1. Tear the non-marking adhesive and attach it to the locking clamps A and B.  
2. Attach the locking clamp A to the wall/surface and press it.  
(Clean the wall/surface before attaching it.)  
3. Attach the locking clamp B to the back of the extension cord.  
4. Push the locking clamp B on the extension cord into the slot of the locking clamp A.

Protective Function

Multiple Circuit Protection

Over-Heat Protection

Short-Circuit Protection

Over-Voltage Protection

Over-Current Protection

Flame Retardant Protection

Attention  

Do not disassemble, puncture, drop, bend or modify

Do not shake while charging

Unplug the device when fully charged

Do not expose to liquids

Keep away from children

Avoid extreme temperatures

3 years warranty

For the fastest and safest charge, use an ADAM cable, your device's original cable or a certified cable (such as MFi).

The information in this user manual may be changed without prior notice, please scan the QR code for the latest version

Cause of appliance fire

Avoid using the extension cord in the following conditions or improper use of the extension cord.

1. The plug is worn and deformed.

2. The plug is aged and turns black.

3. Too many appliances have been plugged to the extension cord and easily leads to overloading.

4. The plug has not been inserted into the socket tightly.

5. Use the plug without extension cord when using heating high power products.

6. Do not tie the extension cord.

ADAM

ADAM elements International Co., Ltd.  
www.adamelements.com  
support@adamelements.com  
+886-2-2738-9900

RoHS

R64847 RoHS

PRINTED WITH SOY INK

日本語

取扱説明書

OMNIA G65

Series

GaN 65W 急速充電用電源ストリップ

仕様

説明: GaN 65W 急速充電用電源ストリップ

定格電圧、周波数、電流  
AC 125V, 50-60Hz, 15A

定格容量 1650W MAX

USB 入力: AC 110V, 50-60Hz, 1.5A max.

USB 合計出力: 65W max.

USB 出力電力:

- USB-C1 / C2 PD: 5-11V≒2.8A(PPS) ; 5-20V≒2.8A(PPS), 5V≒3A; 9V≒3A; 12V≒3A 15V≒3A; 20V≒3.25A
- USB-A1 / A2 QC: 5V≒3A; 9V≒3A; 12V≒3A
- USB-C1 + C2 / USB-C1 + A2: 45W + 20W
- USB-A1 + A2 / USB-A1 + C2: 36W + 20W
- USB-C1 + A1 / USB-C2 + A2: 15W(5V≒3A)
- USB-C1 + (USB-C2 + A2): 45W + 15W
- USB-A1 + (USB-C2 + A2): 36W + 15W
- (USB-C1 + A1)+USB-C2: 15W + 20W
- (USB-C1 + A1)+USB-A2: 15W + 20W
- (USB-C1 + A1)+(USB-C2 + A2): 15W + 15W

操作温度: 0°C - 40°C

サイズ: 210 x 58 x 31.4 mm    重量: 517 g

ケーブル長さ: 1.8m    保証: 3年

\*本製品のアース線は緑色の線です。

含まれるもの

- OMNIA G65 x1
- Mac電源ストリップホルダー
- 取扱説明書

製品紹介

GaN 65W USB急速充電ポートを備えた4口の電源ストリップで、複数のデバイスを同時に充電します。

高出力で安全な電源コード  
国の安全基準に適合したVCTF 2.0mm\*二層絶縁被覆線を使用しています。

PC難燃性素材  
高温に強く、難燃性・耐火性があります。

マスターパワーオフ・オーバーロード自動パワーオフスイッチ  
過負荷になると、自動的に電源がオフになります。高電力消費のデバイスを取り外し、RESETの位置にスイッチを切り替えてください。数分後に正常に使用できるようになります。

防塵・チャイルドセーフティシャッター  
お子様がコンセントに触れないように、またコンセントにホコリが入らないようにしてください。

2 USB-C + 2 USB-A ポート  
複数のデバイスを同時に充電できます。

MacBook Pro 13" と USB-C 65W のノートパソコン

iOS & Android デバイス

ゲーム機

パワー・バンク

雷サージ保護  
落雷などの異常を吸収して高電圧の電流パルスが発生させ、電力供給を安定させ、電気器具を安全に保護します。

独立プッシュスイッチ  
誤って触れないようにしてください。

PTPインジケータライト (プロアクティブサーマルプロテクター)  
インジケータライトが点灯し、デバイスの電源が入っていない保護されていることを示します。コンセントまたはスイッチが異常に高温で、発火点に達しない場合、PTP高温パワーオフ保護機能が作動し、パワーオンインジケータライトが消灯します。PTPが作動すると、コンセントが破損して使用できなくなります。

壁付け用力穴

サージ保護デバイス

サージ吸収電圧: 2500V max. (1.2/50μs)  
サージ吸収電流: Current: 1200A max. (8/20μs)  
サージ吸収エネルギー: 25J max. (10/1000μs)  
\*吸収限度を超えるサージの場合、サージアブソーバが破損し、電気器具を保護できなくなります。

スマート充電IDチップを搭載しています。  
スマート充電: デバイスに必要な電流/電圧は、急速充電のために自動的に識別されます。  
その他のデバイス: USB BC1.2充電仕様を満たす場合、最大1.5Aの充電電流が供給されます。  
機器に充電プロトコルがない場合、USB-AはDCP MODEに対応し、1.0A(通常出力モード)を提供します(USB-Cはプロトコルなしの充電に対応していません)。

警告  
1. 同一の延長コードのコンセントで同時に使用される電気器具の総電力は、過負荷および火災を回避するために、1650Wを超えないものとします。  
2. 本製品は、感電の危険を減らすために、乾燥した場所での屋内使用に限定されています。  
3. 本製品はAC110V電源でのみ使用できます。電気機器の損傷を防ぐため、125Vを超えないようにしてください。  
4. 重大な危険を回避するため、外力を加えないでください。延長コードのスイッチとコンセントは、定期的に点検してください。  
破損、緑さび、粘結、過熱などの異常が発生した場合は、直ちに使用を中止し、交換してください。  
5. PTPが作動しているときは、スイッチをONの位置にできません。

延長コードの電源ストリップホルダーの使用方法  
1. マーキングされていない接着材を破り、係止クランプAとBに取り付けます。  
2. 係止クランプBを壁・壁面に取り付け、押さえます。  
(壁・壁面をきれいにしてから取り付けてください。)  
3. 係止クランプBを延長コードの背面に取り付けます。  
4. 延長コードの係止クランプBを係止クランプAのスロットに押し込みます。

保護機能

多重回路保護

過熱保護

短絡保護

過電圧保護

過電流保護

難燃性保護

ご注意  

穴を開けたり、落したり、曲げたり、解体および改造しないでください

充電中に振動させないでください

充電完了後はデバイスのプラグを抜いてください

液体にさらさないでください

お子様の手の届かないところに保管してください

極端な温度は避けてください

3年保証

最も高速かつ安全に充電するため、ADAMケーブル、デバイス付属ケーブル、または認定済みのケーブル ( MFi ) を使用してください

ユーザーマニュアルについては、パッケージのQRコードをスキャンしてください。

Cause of appliance fire

Avoid using the extension cord in the following conditions or improper use of the extension cord.

1. プラグが摩耗し、変形している。

2. プラグが古くなり、黒く変色している。

3. 延長コードに接続されている電気器具が多すぎると、過負荷になりやすい。

4. プラグがコンセントにしっかりと差し込まれていない。

5. 暖房用高電力機器を使用する場合は、延長コードのないプラグを使用する。

6. 延長コードは縛らないでください。

ADAM

ADAM elements International Co., Ltd.  
www.adamelements.com  
support@adamelements.com  
+886-2-2738-9900

RoHS

R64847 RoHS

PRINTED WITH SOY INK

繁體中文

中文說明書

OMNIA G65

Series

GaN 65W 智慧快充延長線

規格

描述: GaN 65W 智慧快充延長線

額定電壓/頻率/電流  
AC 125V, 50-60Hz, 15A

額定容量: 1650W MAX

USB 輸入: AC 110V, 50-60Hz, 1.5A max.

USB 總輸出: 65W max.

USB輸出功率:

- USB-C1 / C2 PD: 5-11V≒2.8A(PPS) ; 5-20V≒2.8A(PPS), 5V≒3A; 9V≒3A; 12V≒3A 15V≒3A; 20V≒3.25A
- USB-A1 / A2 QC: 5V≒3A; 9V≒3A; 12V≒3A
- USB-C1 + C2 / USB-C1 + A2: 45W + 20W
- USB-A1 + A2 / USB-A1 + C2: 36W + 20W
- USB-C1 + A1 / USB-C2 + A2: 15W(5V≒3A)
- USB-C1 + (USB-C2 + A2): 45W + 15W
- USB-A1 + (USB-C2 + A2): 36W + 15W
- (USB-C1 + A1)+USB-C2: 15W + 20W
- (USB-C1 + A1)+USB-A2: 15W + 20W
- (USB-C1 + A1)+(USB-C2 + A2): 15W + 15W

操作溫度: 0°C - 40°C

尺寸: 210 x 58 x 31.4 mm    重量: 517 g

線材長度: 1.8m    保固: 3 years

\*本產品接地線為綠色線

包裝內含物

- OMNIA G65 x1
- 束線帶 x2
- 3M 雙面膠板
- 產品說明書

產品介紹

配備GaN 65W USB 快速充電的4孔延長線可同時為多個裝置充電。

高功率安全線材  
採用VCTF 2.0mm\*雙層絕緣包覆電線，符合國家安全標準。

PC阻燃材料  
耐高溫、阻燃、防火。

主電源及過載自動斷電開關  
使用超過1650W電流時，會自動切斷電源  
請移除高耗電設備，幾分鐘後切換到RESET位置即可正常使用。

防塵及兒童防護蓋  
避免孩童觸摸插孔及防止灰塵進入。

2 USB-C + 2 USB-A  
同時可充多項裝置。

MacBook Pro 13" & USB-C 65W 筆記型電腦

iOS & Android 裝置

遊戲機

行動電源

防雷突波保護  
能吸收雷擊及其他異常產生高壓電流脈波，穩定電源供應，保護電器安全。

獨立按壓式開關  
避免誤觸。

PTP高溫斷電指示燈  
燈亮為插座正常供電中。當插座或開關異常高溫而未達燃點前，PTP高溫斷電裝置會啟動保護，通電指示燈熄滅。當PTP高溫斷電裝置啟動後，該插座即已被損無法再使用。

掛孔

突波保護裝置

最大突波吸收電壓: 高達2500V (1.2/50μs)  
最大突波吸收電流: 高達1200A (8/20μs)  
最大突波吸收能量: 高達25J (10/1000μs)  
\*若突波超出最大吸收量，突波保護裝置將會損毀，即無法保護電器。

配備Smart Charge ID晶片  
智能充電: 自動辨識裝置所需之電流/電壓進行快速充電  
其他裝置: 符合USB BC1.2充電規範時，提供最大1.5A充電電流。  
若設備本身未具備任何充電協議時，USB-A支援DCP MODE，提供1.0A (正常輸出模式) (USB-C不支援無協議充電)

警告  
1. 在同一延長線的插座上同時使用的電器總功率不可超過1650W，以免過載引發火災。  
2. 本產品僅供室內乾燥地點使用，降低觸電風險。  
3. 此產品僅限AC110V電源使用，且不得超過125V，避免加速電器設備損壞。  
4. 請定期檢查延長線開關及插座，如有破損、出現線露、焦化或過熱等異常狀況，應立即停止使用並更換。  
5. 當PTP啟動後，開關無法定位在ON位置，請勿強加外力通電，以免造成嚴重危險。

延長線固定器使用方式  
1. 撕開無痕膠貼在固定點A、B上  
2. 將固定片A貼在牆上/平面上按壓 (黏貼前須將牆面/平面清除乾淨)  
3. 將固定片B貼在延長線背面  
4. 把延長線上的固定片B推進固定片A的卡槽內即可

防護功能

多重電路保護

過熱保護

短絡保護

過量電壓保護

過電流保護

阻燃材質保護

注意  

請勿拆解、刺穿、摔落、彎折或改造

充電時請勿搖晃

裝置電池充飽後請卸除

請勿接觸液體

遠離孩童

避免高溫或過低環境溫度下使用

3年品質保固

為確保快速且安全的充電品質，請使用ADAM elements的線材、原廠線材或通過認證 (如MFi) 的線材。

紙本說明書版面修改將不另行通知，修改說明請依照影印外印製QR Code為主

電器火災發生原因

避免使用有以下情形之延長線或不當使用方式

1. 插頭磨損變形。

2. 插頭老化變黑。

3. 連接過多電器，容易導致過載。

4. 插頭未緊密插進插座。

5. 在使用加熱型高功率產品時，不要使用延長線，直接插插頭。

6. 不要將延長線纏繞使用。

設備名稱: OMNIA G65 智慧快充延長線    型號 (型式): OMNIA G65    APAADG65SWH  
Equipment name:    Type designation (Type):

| 單元 Unit | 鉛(Pb) | 汞(Mercury (Hg)) | 鎘(Cd) | 六價鉻 hexavalent chromium (Cr <sup>6+</sup> ) | 多環芳烴 polycyclic aromatic hydrocarbons (PAHs) | 多溴二苯醚 polybrominated diphenyl ethers (PBDEs) |
|---------|-------|-----------------|-------|---------------------------------------------|----------------------------------------------|----------------------------------------------|
| 塑膠外殼    | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 線材      | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 內部      | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 充電線電纜   | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 電線      | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| PC板類    | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 充電器線類   | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| LED燈    | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 接插件     | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| USB線類   | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |
| 電源線     | ○     | ○               | ○     | ○                                           | ○                                            | ○                                            |

備考 1: "超出0.1 wt %" 及 "超出0.01 wt %"，係指所用物質之百分比含量超出百分比含量標準值。  
Note 1: "Exceeding 0.1 wt %" and "exceeding 0.01 wt %" indicate that the percentage content of the restricted substance exceeds the reference percentage value of presence condition.  
備考 2: "○" 係指該項所用物質之百分比含量未超出百分比含量標準值。  
Note 2: "○" indicates that the percentage content of the restricted substance does not exceed the percentage of reference value of presence.  
備考 3: "-/-" 係指該項所用物質未使用。  
Note 3: The "-/-" indicates that the restricted substance corresponds to the exemption.

具有智慧辨識功能，若滿足充電裝置之快充協定，則可支援快充功能。  
其他裝置: 符合USB BC1.2充電規範時，提供最大1.5A充電電流。  
若設備本身未具備任何充電協議時，TYPE A支援DCP MODE提供1.0A (正常輸出模式)。(TYPE C不支援無協議充電)。

ADAM

ADAM elements International Co., Ltd.  
www.adamelements.com  
support@adamelements.com  
+886-2-2738-9900

RoHS

R64847 RoHS

PRINTED WITH SOY INK